


Remote Indicator

PA58-3



- **Remote indication of the activation of a conventional or loop detector**
- **Connection of up to 3 remote indicators to one detector**
- **Display for individual detectors or for a group of detectors**
- **Bright, power-saving LED**
- **Supply through the detector line or loop**



Description

The Remote Indicator PA58-3 serves for the remote display of the alarm activation of a fire detector. With that, the activated detector can be located quickly if the status LED on the detector is not visible or if the indicator is placed at a remote site.

That is necessary if, for example, the detector is installed in a false ceiling or false floor, or if the activation of a detector in a hotel room has to be indicated in the corridor.

Depending on the connection, the remote indicator can display the activation of a single detector or of several detectors – e.g., the detectors in a detector zone

– which are combined for a common display.

Furthermore, due to the low current consumption of the Remote Indicator PA58-3, up to 3 indicators can be connected to one detector. These multiple indicators make it easier for the public safety personnel to locate the detector, if, for example, the way to the activated detector leads through several rooms.

The remote indicator is designed for surface mounting on a wall or on a flush-mount installation box with a diameter of 55 or 60mm. The cable can be entered either from behind (via the flush-mount cable entry in the wall piece) or via the cable entry for surface mounting.

Specifications

Operating voltage	Supply through the detector line voltage or loop voltage
Ambient temperature	-30°C to +70°C (no condensation)
Protection class	IP42
Dimensions W × H × D	80 × 80 × 27 (mm)
Colour	white
Weight	42g
Order number	251003
Order name	Remote Indicator PA58-3